

Sorensen XG 1700 Series

1700 W

1700 Watt, 1U Programmable DC Power Supplies

6–600 V

- Industry Leading Power Density
– Up to 1700 Watts in 1U
- Standard Digital Interfaces – USB&RS232/485
- LXI Ethernet and Isolated analog interfaces
- Power Factor Correction-PFC and universal AC input
- “Green” Sleep Mode – Automatically “sleeps” after period of non-use
- Built in sequencing - Unload your system controller
- Programmable fold-back protection delay



2.8–220 A

~

110

220

ETHERNET   RS232

The XG 1700 is an industry leading programmable DC power supply designed for test, production, laboratory, OEM and quality assurance applications. The XG 1700 is a 1700 Watt, 1U programmable power supply with constant voltage and constant current modes, automatic cross-over and numerous features enabling cost effective, easy integration.

Key Features

Easy Integration

XG 1700 has many control and indication signals such as shutdown, constant voltage (CV) vs. constant current (CC) mode indication, OVP, OCP, OTP, and so on. In addition, the logical-high or -low is free selectable. Thus enabling the XG 1700 to replace existing power supplies with little or no system engineering required.

Free selectable analog control range

Most DC power supplies provide a 0 to 5 or 0 to 10 V analog control range to control the DC output from zero to full DC output range. With the XG 1700, the analog control range is free selectable starting at 0V to an upper range between 2V and 10V. In other words, the analog programming interface range is freely adjustable.

Auxiliary DC output channels with control

In many ATE systems one or more low power, fixed voltage supplies are needed to provide electrical power for any periphery within the ATE cabinet. For this purpose, the XG 1700 provides two standard auxiliary DC output channels. Both auxiliary power channels are controllable directly from the front-panel or through SCPI commands. With these channels, it is possible to drive output-disconnect or polarity-reversal relays, without needing a complicated computer controlled relay board.

DC-waveforms through internal sequencing

To allow for extremely fast programming, sequences can be programmed into and stored in memory using standard SCPI commands through USB, RS-232/485, LXI or GPIB.

Variable Fan Speed Control

The XG 1700's innovative approach to fan speed is determined by internal heat sink temperature. This allows the fans to adjust to a constant optimal speed when the output of the supply is being pulsed. This also reduces noise and increases fan life.

Power Saving Standby Mode

When the XG 1700 has been in an idle state, the supply can go into “sleep mode”, much like a computer monitor. This will allow the user to save energy and minimize lab noise. Since an XG 1700 left in sleep mode is still “on” the user will have quicker access to an enabled output.

Key Modes

Output Auto Start Mode (Auto Restart)

The Auto Start mode establishes the state of the output of the power supply after recovery from a complete power cycle (all front panel LEDs are not illuminated), or after recovery from a PC failure or reboot. If Auto Start mode is set to On, the power supply output will return to its previous value. Also, after the loss of any remote digital control, the XG unit will remain active in its last programmed setting and will not disrupt any test process.

Auxiliary Auto Start Mode

The Auxiliary Auto Start mode determines the state of the auxiliary output after a complete power cycle (all front panel LEDs are not illuminated). With Auxiliary Auto Start mode turned to On, the auxiliary output will be activated after the power supply is powered up again.

Foldback Mode

Foldback mode is used to disable the output when a transition is made between the operating modes. The power supply will turn off/disable the output and lock in foldback mode after a specified delay if the power supply transitions into CV mode or into CC mode, depending on the foldback mode settings. This feature is particularly useful for protecting current or voltage sensitive loads. Foldback can be set to trigger a switch when transitioning from CV to CC mode or from CC to CV mode.

AMETEK
Programmable Power
9250 Brown Deer Road
San Diego, CA 92121-2267
USA

AMETEK
PROGRAMMABLE POWER

XG 1700 Series : Product Specifications

1700 W

| Output | | | | |
|-------------|---|--|--|--|
| Models | Output Voltage ¹ | Output Current ² | Output Power ³ | |
| XG 6-220 | 6 V | 220 A | 1330 W | |
| XG 8-200 | 8 V | 200 A | 1610 W | |
| XG 12-140 | 12 V | 140 A | 1690 W | |
| XG 20-84 | 20 V | 84 A | 1690 W | |
| XG 33-50 | 33 V | 50 A | 1660 W | |
| XG 40-42 | 40 V | 42 A | 1690 W | |
| XG 60-28 | 60 V | 28 A | 1690 W | |
| XG 80-21 | 80 V | 21 A | 1690 W | |
| XG 100-17 | 100 V | 17 A | 1710 W | |
| XG 150-11.2 | 150 V | 11.2 A | 1690 W | |
| XG 300-5.6 | 300 V | 5.6 A | 1690 W | |
| XG 600-2.8 | 600 V | 2.8 A | 1690 W | |
| Models | Line Regulation Voltage | Line Regulation Current | Load Regulation Voltage | Load Regulation Current |
| | (0.005% of rated output voltage +2 mV) ⁴ | (0.01% of rated output current +2 mA) ⁵ | (0.005% of rated output voltage + 2 mV) ⁶ | (0.02% of rated output current +5 mA) ⁷ |
| XG 6-220 | 2.3 mV | 24 mA | 2.3 mV | 49 mA |
| XG 8-200 | 2.4 mV | 22 mA | 2.4 mV | 45 mA |
| XG 12-140 | 2.6 mV | 16 mA | 2.6 mV | 33 mA |
| XG 20-84 | 3.0 mV | 10.4 mA | 3.0 mV | 22 mA |
| XG 33-50 | 3.7 mV | 7 mA | 3.7 mV | 15 mA |
| XG 40-42 | 4 mV | 6.2 mA | 4 mV | 13 mA |
| XG 60-28 | 5 mV | 4.8 mA | 5 mV | 10.6 mA |
| XG 80-21 | 6 mV | 4.1 mA | 6 mV | 9.21 mA |
| XG 100-17 | 7 mV | 3.7 mA | 7 mV | 8.4 mA |
| XG 150-11.2 | 9.5 mV | 3.12 mA | 9.5 mV | 7.2 mA |
| XG 300-5.6 | 17 mV | 2.56 mA | 17 mV | 6.1 mA |
| XG 600-2.8 | 32 mV | 2.28 mA | 32 mV | 5.6 mA |
| Models | Output Noise (rms, 300 kHz) | | Output Ripple (p-p, 20 MHz) | |
| | Voltage | Current ⁸ | Voltage | |
| XG 6-220 | 8 mV | 400 mA | 50 mV | |
| XG 8-200 | 8 mV | 340 mA | 50 mV | |
| XG 12-140 | 8 mV | 240 mA | 50 mV | |
| XG 20-84 | 8 mV | 150 mA | 50 mV | |
| XG 33-50 | 8 mV | 120 mA | 50 mV | |
| XG 40-42 | 8 mV | 90 mA | 50 mV | |
| XG 60-28 | 8 mV | 75 mA | 50 mV | |
| XG 80-21 | 8 mV | 50 mA | 80 mV | |
| XG 100-17 | 8 mV | 40 mA | 80 mV | |
| XG 150-11.2 | 10 mV | 32 mA | 100 mV | |
| XG 300-5.6 | 25 mV | 20 mA | 150 mV | |
| XG 600-2.8 | 50 mV | 12 mA | 250 mV | |

1. Minimum output voltage is guaranteed to be $\leq 0.2\%$ of the rated voltage at zero output setting.

2. Minimum output current is guaranteed to be $\leq 0.4\%$ of the rated current at zero output setting when measured with rated load resistance.

3. Total output power is also based on AUX1 Output Voltage (5V) and AUX1 Output Current (0.5 A) and AUX2 Output Voltage (15 V) and AUX2 Output Current (0.5 A).

4. From 85-132 Vac or 170-265 Vac, constant load.

5. From 85-132 Vac or 170-265 Vac, constant load.

6. From no load to full load, constant input voltage.

7. For load voltage change, equal to the unit voltage rating, constant input voltage.

8. For 6 V models the ripple is measured at 2-6 V output voltage and full output current. For other models, the ripple is measured at 10-100% output voltage and full output current.

Note: All specifications are subject to change.

XG 1700 Series : Product Specifications

| Model | Maximum Recommended Remote Sense Line Drop Compensation per Line ⁹ | Up-prog. Response Time, 0~Vmax ¹⁰ | Efficiency ¹¹ (100/200 VAC input) |
|-------------|---|--|---|
| XG 6-220 | 1 V | 60 ms | 76/78% |
| XG 8-200 | 1 V | 60 ms | 77/79% |
| XG 12-140 | 1 V | 60 ms | 81/84% |
| XG 20-84 | 1.5 V | 60 ms | 82/85% |
| XG 33-50 | 2 V | 60 ms | 83/86% |
| XG 40-42 | 2 V | 60 ms | 83/87% |
| XG 60-28 | 3 V | 60 ms | 84/88% |
| XG 80-21 | 5 V | 100 ms | 84/88% |
| XG 100-17 | 5 V | 100 ms | 84/88% |
| XG 150-11.2 | 5 V | 100 ms | 84/88% |
| XG 300-5.6 | 5 V | 150 ms | 84/88% |
| XG 600-2.8 | 5 V | 250 ms | 84/88% |
| Model | Down-prog. Response Time: Full Load* | Down-prog. Response Time: No Load* | Over-Voltage Trip Point |
| XG 6-220 | 50 ms | 300 ms | 0.5–7.5 V |
| XG 8-200 | 50 ms | 400 ms | 0.5–10 V |
| XG 12-140 | 50 ms | 500 ms | 1–15 V |
| XG 20-84 | 50 ms | 600 ms | 1–24 V |
| XG 33-50 | 50 ms | 700 ms | 2–39 V |
| XG 40-42 | 50 ms | 800 ms | 2–44 V |
| XG 60-28 | 50 ms | 900 ms | 3–66 V |
| XG 80-21 | 80 ms | 1000 ms | 3–95 V |
| XG 100-17 | 100 ms | 1200 ms | 3–125 V |
| XG 150-11.2 | 150 ms | 1800 ms | 3–180 V |
| XG 300-5.6 | 150 ms | 2200 ms | 5–330 V |
| XG 600-2.8 | 250 ms | 3500 ms | 5–660 V |

9. When using remote sense, the total of the load voltage and the load line drops must not exceed the rated output of the power supply. For example, for an XG 6-220 in an application with 1 V of load line loss (0.5 V/Line), the maximum available load voltage would be 6-1=5 V. Note: The unit may operate at higher output voltages than this, but there is no guarantee that the power supply will meet performance specifications. Ultimately, the upper limit of the output voltage will be determined by internal circuitry of the power supply (non-adjustable)

10. With rated, resistive load.

11. At 100/200 Vac input voltage and maximum output power.

Applies to all footnotes: Programming and Readback: RS-232, RS-485, USB built in. GPIB, Ethernet optional. Specifications are guaranteed from 1% to 100% of the rated output voltage, current, and power.

* Typical

Note: All specifications are subject to change.

XG 1700 Series : Product Specifications

1700 W

| AC Line Input Specifications | | | |
|---|---|--|--------------------------------------|
| Rated AC Input Voltage/Frequency | 100–240 Vac, 47–63 Hz | | |
| Operational AC Input Voltage/Frequency | 85–265 Vac continuous, 47–63 Hz, single phase | | |
| Input Current (at 100/200 Vac) | 23/12 A | | |
| Inrush Current (100/200 Vac) | Less than: 50 A | | |
| Power Factor Correction | 0.99@100/200 Vac, rated output power | | |
| Programming Mode | APG | ISOL | Digital |
| Voltage & Current Output Voltage Programming | 0-100% 2~up to 10 V, programmable | | |
| Voltage & Current Output Resistive Programming | 0-100% 2~up to 10 k Ω , programmable | | |
| Voltage Output Resistor Programming | 0-100% 2~up to 10 k Ω , programmable | | |
| Output Voltage and Current Monitor | 0-100% 2~up to 10 V, programmable | | |
| Voltage Programming Accuracy (mV) ¹ | \pm 0.5% of rated output voltage, max (0-4V/4K range) | | \pm 0.1% of rated output voltage |
| Current Programming Accuracy (mV) ¹ | \pm 1% of rated output current, max (0-4V/4K range) | | \pm 0.2% of rated output current |
| Voltage Readback Accuracy (mV) | \pm 1% of rated output voltage | | \pm 0.1% of rated output voltage |
| Current Readback Accuracy (mV) | \pm 1% of rated output current | | \pm 0.2% of rated output current |
| Isolation (Prog and Readback Lines) | With respect to chassis potential: 500 V | With respect to: chassis potential: 600 V negative or positive main output 1500 V negative or positive auxiliary output 300 V | |
| Voltage and Current Programming Resolution | | | 0.012% of full scale |
| Voltage and Current Readback Resolution | | | |
| Parallel Operation | Up to 4 units in master / slave | Up to 4 units in master / slave | Up to 4 units in master / slave |
| Series Operation | | Up to 2 units (with external diodes) | Up to 2 units (with external diodes) |
| Constant Voltage (CV) Constant Current (CC) Indicator | CV: TTL High (4-5 V) CC TTL Low (0-0.6 V) | | |
| Shutdown Control ² | | Logic low 0.0 - 1.4 V Logic high 2.0 - 15 V Dry contact compatible | |
| AUX On/Off Control | | TTL level or dry contact compatible | |
| Power Supply Status Signal | | TTL high: OK (4-5 V) TTL low: fail (0-0.6 V) | |
| Interlock Enable/Disable | | Dry contact. Open/Short: On or Off programmable | |

1. Typical APG or isolated APG accuracy can be improved to max accuracy by user calibration at the specific range selected

2. The shutdown input has user selectable negative logic operation via front panel or remote digital input/output

Note: All specifications are subject to change.

XG 1700 Series : Product Diagram

1700 W

